



# DIGITAL STROBOSCOPE, push keyboard setting

## Model : DT-2269

### FEATURES

- \* DT-2269 is a microprocessor circuit design, high accuracy, digital readout STROBOSCOPE. Adjusting the "Flash Rate" by push button keyboard, unique design in the world, easy operating & with intelligent function. That is ideal for inspecting and measuring the speed of moving gears, fans, centrifuges, pumps, motors and other equipment used in general industrial maintenance, production, quality control, laboratories and as well as for schools and colleges for demonstrating strobe action.
- \* External trigger input.
- \* RS232 computer interface output.

### SPECIFICATIONS

Display	14 mm (0.56") LED, 6 digits.	Data output	RS 232 computer interface.	
Set up unit	Flash rate - RPM/FPM, Hz * FPM - flash per minute.	Power supply	AC 110V 10%, 50/60 Hz. or AC 220V 10%, 50/60 Hz. or AC 230V 10%, 50/60 Hz.	
Flash rate set up range	RPM 20 to 10,500 RPM/FPM. Hz 0.3 to 175 Hz	Circuit	This stroboscope/tachometer employs an custom one-chip of microcomputer LSI circuit & crystal control time base which results in extraordinary accuracy & high set up stability over a wide, dynamic range.	
Resolution (internal trigger)	RPM/ FPM 0.1 RPM/FPM < 1,000 RPM/FPM. 1 RPM/FPM 1,000 RPM/FPM	Power consumption	Less than 30 Watt.	
	Hz 0.001 Hz < 10 Hz 0.01 Hz 10 Hz - 99.99 Hz 0.1 Hz 100 - 175 Hz			
	Operating temp.			0°C to 50°C (32°F to 122°F).
	Operating humidity			Less than 80% R.H.
Accuracy	± (0.15 % + 1d). < 4,000 RPM/FPM ± (0.5 % + 1d). 4,000 RPM/FPM	Dimension	HWD - 21 x 12 x 12 cm (8.3x4.8x4.8 inch).	
Set up stability	1 digit within 10 minute.	Weight	1 Kg/2.2 LB.	
Switch Select Function	RPM, Hz Fine adjust, Coarse adjust, Multiply by 2, Divide by 2, Fast finder, Memory recall.	Housing case	Compact and impact plastic injection case with plastic mirror type reflector.	
External trigger	Input signal : 5V to 30 V rms, 20 to 10,500 RPM/FPM. 0.3 to 175 Hz	Calibration	Crystal time base and microprocessor circuit, not necessary take any external calibration procedure if the stroboscope working properly.	
Memory	Can memorize 2 sets of measuring data.	Accessories included	Operation manual..... 1 PC. Power cord.....1 PC.	
Operating duty Cycle	For prolong life and safe operation, please adhere to the following duty cycle: < 2000 RPM - 2 hours,                      2000 to 3600 RPM - one hour, 3601 to 8000 RPM - 30 minutes,        > 8000 RPM - 10 minutes. * 10 min. cooling off period between cycles.			

### FLASH TUBE SPECIFICATIONS

Flash tube	Xenon lamp.	Flash tube replacement	It is required to change the flash tube when the instrument start to flash irregularly at speeds of 3600 RPM/FPM or more.
Flash Duration	Approximately 60 to 1,000 microseconds.		
Flash color	Xenon white 6,500 K degree.		
Flash energy	4 Watts-seconds (joules).		
Beam Angle	80 degrees.		

### OPERATIONS PROCEDURES

Preparation	(a) Plug unit into a properly grounded 110V AC, 220V AC or 240V AC outlet. (b) Turn the power switch to " on " position. (c) Determine the range switch to " Low " or " High " position.
Checking Speed	When checking speed, care must be taken to insure that the strobe is flashing in unison (one to one) with the object being monitored. A Stroboscope will also stop motion at 2:1, 3:1, 4:1 et., this is normally referred to as harmonics. To be sure of unison, turn the dial until two images appear - this will double the actual speed. Then lower the flashing rate until a single and stationary image appears - this is the actual true speed.
Checking Motion	For motion analysis, simply locate the actual speed as mentioned above and then turn the dial slowly up or down. This will give a slow motion effect allowing complete inspection.

**Reset** When order the stroboscope, should inform the power supply type is AC 110V, or 220 V or 230V.

\* Appearance and specifications listed in this brochure are subject to change without notice. CAT B200699