AY-C19 / AY-D19 26-Bit Wiegand Prox & Pin Reader

The AY-C19 and AY-D19 Prox & Pin Readers are available in 26-Bit Wiegand Format, in both Mullion and US Gang Box sizes.

AY-C19



- ➤ 26-Bit Wiegand Reader
- ➤ Reading Distance: 6 to 8cm
- ► RF Modulation: ASK at 125 kHz
- ➤ For indoor use
- ➤ Slim Stylish Design (Mullion)
- ➤ Bi-Color Light Indicator
- ➤ Audible Buzzer Indicator
- ➤ Built in Tamper
- ➤ Includes Bell Button
- ➤ Size: 130mm x 42mm x 18mm

SEE BELOW FOR COMPATIBLE CONTROLLERS

- ➤ 26-Bit Wiegand Reader
- ➤ Reading Distance: 8 to 10cm
- ➤ RF Modulation: ASK at 125 kHz
- ➤ For indoor use
- ➤ Slim Stylish Design (USA Gang Box)
- ➤ Bi-Color Light Indicator
- ➤ Audible Buzzer Indicator
- ➤ Built in Tamper
- ➤ Includes Bell Button
- ➤ Size: 122mm x 75mm x 24mm

SEE BELOW FOR COMPATIBLE CONTROLLERS

<u>AY-D19</u>



26-Bit Wiegand Controllers



AC-015 26-Bit Wiegand Single Door Controller



AC-020 26-Bit Wiegand Two Door Controller



AC-115
26-Bit Wiegand
Single/Multi Door
Controller

Dealer Information Box:

Copyright Rosslare Enterprises Ltd 1999.





