

Digital Multimeter PS8a

PS8a

General Information

3-3 / 4 digits 4000 count

0.7% best accuracy

Range hold

Auto power off (15min)

Low power ohm (input voltage 0.4V)

Power saving design

Pocket notebook size

Solar battery DMM



General Specification



Function	Measuring range	Best accuracy	Resolution	Input impedance
DCV	400m/4/40/400/500V	$\pm (0.7\%+3)$	0.1mV	DCV: 10M \sim 100M Ω
ACV	4/40/400/500V	$\pm (2.3\%+10)$	0.001V	ACV: 10M \sim 11M Ω
Resistance	400/4k/40k/400k/4M/40M Ω	$\pm (2.0\%+5)$	0.1 Ω	
Continuity	Buzzer sounds at less than 10 \sim 120 Ω . Open voltage : 0.4V			
Diode test	Open voltage : approx. 1.5V			
Bandwidth	40 \sim 400Hz			
Battery	Amorphous solar battery + manganese dioxide lithium secondary battery			
Size / Weight	H115XW57XD18mm/approx. 85g			
Standard accessories included	Instruction manual			

